

Firmware para o Receptor TDT Strong modelo SRT8105 ECO.

VERSÃO FIRMWARE

- [SRT8105ECO_V1.0.4_20120307.abs](#)

MELHORIAS

- Size of .srt subtitle files
- Progress bar was added in the infobanner
- Default setting for HDMI output is set to 720P
- Volume adjustment > the step function was removed
- LCN is set to ON for Poland
- Improvement of Signal banners
- Improvement of Polish, German and Czech OSD (menu text)
- Strange effect in Channel sort/edit menu is fixed when PIN is requested
- The "First Audio" and " Second Audio" selection is now followed correctly
- Correction of auto scan for Poland
- Fix for time zone (when language was changed, time zone changed as well)

PROCEDIMENTOS

a) At the PC:

- Extract the .abs file from the package to the root directory of the connected USB device. Then disconnect the USB device from the PC and connect it to the receiver.

b) At the Receiver:

After the USB device has been detected successfully, you can perform the software update according to the following steps:

1. Press **MENU** button to enter Main Menu. Select *Tools* with the "**up/down**" buttons and press **OK** to enter.

2. After entering Tools menu use the "**up/down**" buttons and select *Upgrade by USB* and press **OK**.
. Software Upgrade menu is shown.

3. Use the "</>" buttons to select *AllCode* item and the "**up/down**" buttons to select the *Upgrade File*.
With the "**up/down**" buttons select the correct update file. Now use the "**up/down**" buttons to select *Start* and press

OK

to start the update process.

4. After the software file is loaded you will be asked if you want to burn flash. Select **Yes** to update your receiver or

No

to cancel. Then press

OK

to perform the desired action.

NOTA - Durante o processo de UPDATE NUNCA desligue o receptor da fonte de alimentação nem no botão ON/OFF, nem retire a PEN USB! Isso poderá danificar o seu equipamento de forma irremediável e perderá a garantia!